



FEATURES

- **WIDE VOLTAGE RANGE:** 2 – 30 VDC
REVERSE POLARITY PROTECTION
SURGE PROTECTION
- **LOW CURRENT CONSUMPTION:** 100 μ A
- **WIDE BANDWIDTH:** 1 kHz
- **OPEN DRAIN SINKING, 100V / 100 mA OUTPUT**
REVERSE POLARITY PROTECTION
- **HIGH SENSITIVITY**
CUSTOM SENSITIVITY BY SPECIAL ORDER
- **HIGH HYSTERESIS**
CUSTOM HYSTERESIS BY SPECIAL ORDER
- **OMNIPOLAR:** WORKS WITH EITHER NORTH
OR SOUTH POLE OF THE MAGNET
- **SPECIAL VERSIONS WITH A PULSE DIVISION
FACTOR AVAILABLE**



1. DESCRIPTION

The GMS300 is a precision micro power wide voltage range magnetic pick-up sensor with very high sensitivity and hysteresis, designed for harsh industrial environment. Its sensitivity and hysteresis can be easily changed at the factory and made by customer requirements.


The sensor works with either north or south pole of the magnet.

When the magnetic field exceeds its operate point the open drain output will turn on and sink current up to 100 mA DC. When the field decreases and reaches the release point the output will turn off and stand voltage up to 100 V DC. The high hysteresis between both trigger levels (operate and release) provides high noise immunity and reliability.

GMS300 is ideal for battery power applications with its unmatched combination of low voltage, high sensitivity and hysteresis and low current consumption but still the best choice for any other application providing wide voltage range of operation, high output current, reverse polarity and surge protection.

APPLICATIONS

- **RPM MEASUREMENT**
- **PADDLE WHEEL, IMPELLER, PROPELLER,**
TURBINE FLOW METERS
- **POSITIONING**
- **OBJECTS COUNTING**
- **RAIN GAGES**
- **WIND SPEED METERS**
- **BATTERY POWER DEVICES**





2. ABSOLUTE MAXIMUM RATINGS *

Operating temperature	-40 °C to +85 °C
Higher temperature versions available by special order.	
Voltage on red wire with respect to black wire	+/- 42 VDC
Voltage on white wire with respect to black wire	100 VDC
Maximum output current sunk (into white wire – out of black wire)	100 mA DC

*** NOTICE: Stresses above those ratings may cause permanent damage to the device.**

3. CHARACTERISTICS

Parameter	Conditions	Typical	Units
Power Supply Voltage RECOMMENDED	-40 to + 85 °C	2 – 40 2.3 - 30	VDC
Supply Current	2.0 – 21.5 V DC, output open, Fig. 1	100	uA
Sensitivity	Alnico 5, 0.305" x 0.060", 25 °C, 2.3 - 30V, Fig. 2, Fig. 3	98 - 100	%
Input Frequency	Fig. 4, Fig. 5	0 – 1000	Hz
Materials	Body from Ertalyte ® PET-P. Epoxy potting.		
Cable	6' (1.80 m) PVC 3-wire, 22 AWG each. Black, red and white.		




Fig. 1 Consumption vs. Power Supply




Fig. 2 Sensitivity vs. Power Supply




Fig. 3 Sensitivity vs. Distance




Fig. 4 Sensitivity vs. Frequency




Fig. 5 Input Frequency Test

4. APPLICATION

4.1 MECHANICAL

GMS300 works by sensing magnetic field. It is important that it has to be provided a strong enough magnetic field for the operate point and weak enough or absent magnetic field for the release point.

The moving object that is to be sensed has to provide a constant (DC) magnetic field by having built-in small permanent magnet or a DC current coil. The direction of that field has to be axial to the GMS300 as shown on Fig. 6 .

The sensor has to be mounted on non-magnetic materials such as plastics, brass, stainless steel etc. Materials like cast iron can magnetize and affect the performance of GMS300. It also has to be mounted away from devices producing magnetic field (transformers, electric motors, breakers).




Fig. 6 GMS300 and magnetic field interaction

Figure 7 shows dimensions important for mounting the sensor.




Fig. 7 Dimensions of GMS300

NOTE: DO NOT OVER TIGHTEN THE SENSOR.

Figure 8 shows a typical application of GMS300. The paddle wheel has molded small permanent magnets in its fins and it is rotated by the liquid flowing through the flow meter. GMS300 picks up the pulses of the magnetic field and provides a clear and reliable signal for a flow computer / totalizer.

The same principle of operation can be used to measure RPM of a rotating object.




Fig. 8 RPM or flow measurement

There are many other applications such as positioning, counting objects, wind speed measurement, rain gage equipment, automatic door opening etc. where GMS300 can be an excellent solution.

4.2 ELECTRICAL

GMS300 is a 3-wire device. Black wire is the common, red wire is the power supply and white wire is the sinking open drain output. It requires a pull-up resistor to limit the current below 100 mA.

Many instrumentation devices, totalizers, displays, controllers, computers etc. have a built-in pull-up resistor. In such a case the external resistor is not needed. If the sensor is to be connected to a PLC a “current sourcing input” of the PLC has to be used.

Figure 9 shows connections of GMS300 to [GFC100](#) micro power flow computer / RPM computer / totalizer which powers the sensor and displays accurate flow rate, total or RPM and provides many programmable features.

GMS300 can also be used with [GFC110](#) flow computer / RPM computer / totalizer which has in addition an isolated 12 bit analog 4-20 mA output and isolated no polarity pulse output.




Fig. 9 [GFC100/110](#) powers GMS300

Figure 10 shows typical connections to displays, totalizers, process indicators, computers, regulators etc. using one power supply.




Fig. 10 Typical connections with one PS

Figure 11 shows typical connections using two power supplies and internal pull-up resistor.




Fig. 11 Using two PS and an internal pull-up



NOTE: Special versions of GMS300 with a pulse division factor are available

5. ORDERING

For ordering please use G Instruments part number (PN) 30051.

For special versions (division factor, higher temperature range etc.) the part number will be different and will depend on the particular customer's application.



IMPORTANT NOTICE

G Instruments reserves the right to make corrections, modifications, enhancements, improvements, and other changes to its products at any time without notice.

Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

G Instruments does not assume any liability arising from the use of any device or circuit described herein, nor does it convey any license under its patent rights or the rights of others.

Customers are responsible for their products and applications using G Instruments devices. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

G Instruments products are not authorized for use as critical components in life support devices or systems without express written approval of G Instruments.

Trademarks and registered trademarks are the property of their respective owners.